



# StorNext M330 Metadata Appliance

## 4.3.2 Release Notes

---

---

### Purpose of this Release

The StorNext M330 combines industry-proven Quantum hardware and StorNext software into one convenient, out-of-the-box solution. Your M330 system has been pre-installed and is ready to operate with a minimum of additional configuration.

For upgrading to StorNext 4.3.2 on the M330 Metadata Appliance, refer to the “Update Firmware” section of Chapter 7 of the current version of the StorNext User’s Guide.

This document contains additional information related to your M330 system.

For the complete list of documentation for the M330 Metadata Appliance, click the **Documentation** tab on the following web page:

<http://www.quantum.com/ServiceandSupport/SoftwareandDocumentationDownloads/M330/Index.aspx?whattab=Third>

StorNext 4.3.2 is a maintenance release of StorNext software and includes important bug fixes.

The complete list of documentation for StorNext 4.3.2 can be found here (click the “Select a StorNext Version” menu to view the documents for that version of StorNext):

<http://www.quantum.com/ServiceandSupport/SoftwareandDocumentationDownloads/SNMS/Index.aspx?whattab=Fourth>



---

## About This Release

This section contains important things you should know about your M330 Metadata Appliance.

---

### M330 Metadata Appliance

---

The StorNext M330 is designed to run the MDC file system and, optionally, with the StorNext Storage Manager installed. The Gateway server and the Distributed Data Mover features are not supported for installation directly on the M330, but is fully supported when running on a separate client.

---

### Data Replication and Deduplication

---

The M330 supports the use of an optional StorNext replication license. Replication throughput is limited to a single GbE port.

The M330 is not designed for deduplication, and the standard StorNext deduplication license is not supported with the M330.

---

### StorNext Software Features Supported

---

With the exceptions noted above, all other optional StorNext software is supported on the M330, and is purchased separately.

---

### M330 Metadata Appliance File System Restrictions

---

The M330 does not support running NFS, or CIFS/SAMBA directly on the Metadata Appliance.

---

### M330 Hardware Expansion

---

Although your M330 comes with unfilled expansion slots and drive bays, other hardware upgrades are not supported.

---

### Linux Device Mapper Multipath Support

---

For the StorNext M330 Metadata Appliance - StorNext 4.3.2 and later supports the standard Linux Dynamic Multipath Mapping driver (DMMP) for the metadata array and additional storage. For most configurations, the upgrade process will automatically configure the DMMP settings. If a multipath.conf file is already configured on the system, a RAS ticket will be generated and the upgrade process will be halted. Please contact Quantum Customer Support for resolution assistance. In addition:

- Ensure that the `/etc/multipath.conf` file is identical on both the primary and secondary nodes of the MDC HA pair. (See CR [40015](#) in [Table 1](#) on page 5.)

## Configuring Clients for the M330

In order to prevent a split-brain condition between the HA pair of MDCs on the M330, at least one additional StorNext client must mount the HA file system. This will allow the additional client to "vote" in the event of a split-brain condition.

Because the shared file system on the M330 is on the internal RAID and not visible, you must mount the client using the "diskless=yes" option.

On Linux systems, put into the /etc/fstab an entry similar to this:

```
shared-02637 /stornext/shared cvfs diskless=yes 0 0
```

(The name "shared-SV1249CKD29435" used in the example will vary. The format is "shared-NNNNNNNNNNNNNNNN")

On Windows clients, use the Mount Options field to add "diskless=yes".

For more information about this procedure, refer to the HA chapter in the *StorNext User's Guide*.

---

**Note:** You need to do this on only one client machine.

---

## Target Reset and Fiber Channel Tape Support on Qlogic HBAs

The Enable SCSI Bus Target Reset parameter is enabled by default on all Fiber channel HBAs. The parameter exists for disk arrays, but poses a problem for tape drives.

### PROBLEM

When the SCSI bus target (the tape drive) is reset when a backup job is running, the backup job may abort. If the tape drive does not receive the rewind and unload commands from the backup job, it leaves the tape in the drive. This may cause the drive to be seen as not ready, and then be marked offline in the backup application when the next job tries to use the drive.

### SOLUTION

To disable Target Resets on the tape SAN port on the M330, the following commands can be run on each node.

- 1 Connect to each node via ssh and login using the "stornext" user ID.
- 2 Change to root user permissions by running "sudo rootsh"
- 3 Disable Target Resets on the tape SAN port by issuing "/usr/local/bin/scli -n 1 TR 0"
- 4 Confirm that the setting is correct by issuing "/usr/local/bin/scli -c" and comparing the output for Port 2. It should look like:

```
[root@Acadia1-1 scripts]# scli -c
-----
-----
HBA Instance 0: QLE2562 Port 1 WWPN 21-00-00-1B-32-9D-4A-8D PortID 00-00-00
-----
Connection Options          : 2 - Loop Preferred, Otherwise Point-to-Point
```

Data Rate : Auto  
Frame Size : 2048  
Hard Loop ID : 0  
Loop Reset Delay (seconds) : 5  
Enable Host HBA BIOS : Disabled  
Enable Hard Loop ID : Disabled  
Enable FC Tape Support : Enabled  
Operation Mode : 0 - Interrupt for every I/O completion  
Interrupt Delay Timer (100ms) : 0  
Execution Throttle : 65535  
Login Retry Count : 8  
Port Down Retry Count : 30  
Enable LIP Full Login : Enabled  
Link Down Timeout (seconds) : 30  
Enable Target Reset : Enabled  
LUNs Per Target : 128  
Enable Out Of Order Frame Assembly: Disabled

-----  
-----  
HBA Instance 1: QLE2562 Port 2 WWPN 21-01-00-1B-32-BD-4A-8D PortID 00-00-00  
-----

Connection Options : 2 - Loop Preferred, Otherwise Point-to-Point  
Data Rate : Auto  
Frame Size : 2048  
Hard Loop ID : 0  
Loop Reset Delay (seconds) : 5  
Enable Host HBA BIOS : Disabled  
Enable Hard Loop ID : Disabled  
Enable FC Tape Support : Enabled  
Operation Mode : 0 - Interrupt for every I/O completion  
Interrupt Delay Timer (100ms) : 0  
Execution Throttle : 65535  
Login Retry Count : 8  
Port Down Retry Count : 30  
Enable LIP Full Login : Enabled  
Link Down Timeout (seconds) : 30  
Enable Target Reset : Disabled  
LUNs Per Target : 128  
Enable Out Of Order Frame Assembly: Disabled

## Known Issues

[Table 1](#) lists the known issues for the StorNext M330 Metadata Appliance:

Table 1 Known Issues

Operating System	CR Number	SR Number	Description	Workaround (if applicable)
All	40015	n/a	The M330 <code>/etc/multipath.conf</code> file needs to be identical on both the primary and secondary nodes of the HA pair for failover to work properly.	Copy the <code>/etc/multipath.conf</code> file into the same directory on both MDC nodes of the M330 system any time changes are made to the file.
All	38419	n/a	In the GUI, the reset button on the <b>Configuration &gt; System -&gt; Network</b> tab doesn't always restore current network configuration values.	When this happens, navigate away from the page by selecting any other menu item and navigate back again to reload the current network settings.
	27490/ 37166	n/a	The <code>sn_metrics</code> database tables are not installed in the MySQL database when upgrading to StorNext 4.2.1.0.1 from an earlier version.	After upgrading to 4.2.1.0.1 or later, start StorNext Storage Manager and run the <code>sngateway_install_mysql_tables</code> script: <ol style="list-style-type: none"> <li>1. <code>./usr/adic/.profile</code></li> <li>2. <code>service cvfs start</code></li> <li>3. <code>./usr/cvfs/install/sngateway_install_mysql_tables.pl</code></li> </ol> Optionally, you can verify that the <code>sn_metrics</code> tables have been installed by running <code>mysqlshow</code> : <ol style="list-style-type: none"> <li>4. <code>./usr/adic/mysql/bin/mysqlshow sn_metrics</code></li> </ol>
All	38291	n/a	In an HA failover, an Admin Alert is issued if the new primary MDC attempts to initiate an <code>fs_fmover</code> process on the new standby MDC while the standby MDC is still being rebooted.	Once the impacted standby MDC finishes rebooting and becomes functional again, use <code>fsddmconfig</code> (or the GUI) from the master MDC to re-enable DDM for the standby MDC, as follows: <pre># fsddmconfig -u -s e standby_mdc_hostname</pre>

Operating System	CR Number	SR Number	Description	Workaround (if applicable)
All	29483/ 38267	n/a	Logical and physical Fibre Channel port numbers may not match.	There is no current workaround for this issue. This will be fixed in a future StorNext release.
Linux	37538	1398524	GUI is unable to down a stripe group when LUNs are unavailable	Mark stripe groups down in the GUI before taking the stripe group's disks offline. If that is not possible, set the stripe group down directly through the FSM configuration file and restart the FSM. See the <b>snfs_config(5)</b> man page or the MAN Pages Reference Guide for details.
Linux	38128	1395540	Using the GUI while a large Media import is kicked off via the command line can cause the GUI to timeout or crash.	Wait until a bulk load from tape is finished prior to opening the StorNext GUI.
Linux	29098/ 37916	n/a	Admin alerts are generated for network or FC ports that are disconnected but are configured in the system.	The only way to prevent these alerts from displaying is to remove the network or FC ports that are disconnected from your configuration, unless the ports will only be down temporarily.

---

## Contacting Quantum

More information about this product is available on the Quantum Service and Support website at [www.quantum.com/ServiceandSupport](http://www.quantum.com/ServiceandSupport). The Quantum Service and Support website contains a collection of information, including answers to frequently asked questions (FAQs). You can also access software, firmware, and drivers through this site.

For further assistance, or if training is desired, contact Quantum Technical Assistance Center.

<b>North America</b>	1 800-284-5101 (toll free) 1-720-249-5700
<b>EMEA</b>	+00800 7826 8888 (toll free) +49 6131 3241 1164
<b>APAC</b>	1-800-7826-8887 (toll free) +603-7953-3010
<b>Service and Support Web Site</b>	<a href="http://www.quantum.com/ServiceandSupport">www.quantum.com/ ServiceandSupport</a>
<b>Online Service Request System</b>	<a href="http://www.quantum.com/OSR">www.quantum.com/OSR</a>

(Local numbers for specific countries are listed on the Quantum Service and Support Website.)

---

Product of USA.

Quantum Corporation provides this publication "as is" without warranty of any kind, either express or implied, including but not limited to the implied warranties of merchantability or fitness for a particular purpose. Quantum Corporation may revise this publication from time to time without notice.

#### **COPYRIGHT STATEMENT**

© 2013 Quantum Corporation. All rights reserved.

Your right to copy this manual is limited by copyright law. Making copies or adaptations without prior written authorization of Quantum Corporation is prohibited by law and constitutes a punishable violation of the law.

#### **TRADEMARK STATEMENT**

Quantum, the Quantum Logo, Backup. Recovery. Archive. It's What We Do., Be Certain, Be Quantum Certain, DLT, the DLT Logo, DLTSage, DLTtape, the DLTtape Logo, DXi, DXi Accent, Dynamic Powerdown, FastSense, FlexLink, GoProtect, GoVault, iLayer, Lattus, MediaShield, Optyon, Pocket-sized., Well-armed., Preserving the World's Most Important Data. Yours., Q-Cloud, Quantum Certain, Quantum Certainty, Quantum vmPRO, Scalar, SDLT, SiteCare, SmartVerify, StorageCare, StorNext, Super DLTtape, SuperLoader, and Vision are either registered trademarks or trademarks of Quantum Corporation and its affiliates in the United States and/or other countries. All other trademarks are the property of their respective owners.

Products mentioned herein are for identification purposes only and may be registered trademarks or trademarks of their respective companies. All other brand names or trademarks are the property of their respective owners.

Quantum specifications are subject to change.