

DXi V5000, DXi4800, and DXi9000 Series Release Notes 4.9

Product/Software Release Date January 2024

Contents

Purpose of This Release	2
Product Compatibility List	3
Resolved Issues	5
Known Issues	6
Documentation	7
Supported Backup Applications	7
DXi Additional Notes	7
Contacting Quantum	8

© 2024 Quantum Corporation. All rights reserved. Your right to copy this manual is limited by copyright law. Making copies or adaptations without prior written authorization of Quantum Corporation is prohibited by law and constitutes a punishable violation of the law. ActiveScale, DXi, DXi Accent, FlexSync, FlexTier, iLayer, Lattus, Quantum, The Quantum Logo, QXS, Scalar, StorNext, SuperLoader, Vision, and Xcellis are either registered trademarks or trademarks of Quantum Corporation and its affiliates in the United States and/or other countries. All other trademarks are the property of their respective owners. Quantum specifications are subject to change.

Purpose of This Release

The DXi 4.9 Software release supports DXi4800, DXi9000/9100, and DXi V5000 disk backup systems.

- Note:** This release was scanned for vulnerabilities using Nessus® for vulnerability risk management, as part of Quantum's Quality Assurance (QA) process. The release code build was validated as secure.

What's New in DXi 4.9?

This software release features the following new features and updates:

- DXi Cloud Share** – DXi Cloud Share is a feature that is available in DXi Software 4.9 and above. Cloud Share allows DXi4800 and DXi9000/91000 systems to store de-duplicated backup data sets to any S3 compliant public or private cloud; providing up to 70 times more efficient use of cloud storage space. DXi4800 appliances must be sized at 45 TB or greater to enable Cloud Share (96 GB total memory is required for Cloud Share, which is included in a DXi4800 45 TB or larger system).
- RestAPI Update** – RestAPI version 1.2.6 is available in this release.
- Independent Software Vendor (ISV) Support** - ISV support added for Veeam, NetBackup (NBU), and Backup Exec (BUE) OST.
- Various maintenance updates and bug fixes.**



WARNING: Systems currently using DXi Software versions earlier than 4.5.0.3 MUST UPGRADE TO 4.5.0.3 before upgrading to version 4.9. In general, Quantum strongly recommends upgrading to the latest version of DXi software before installing capacity upgrades, regardless of the capacity increment.

DXi Password Requirements

- System Users** - Passwords must be between 8-64 characters, and must include at least one upper case (A-Z), one lowercase (a-z), one number (0-9), and one special character (` ~ ! @ # \$ % ^ & * () - _ = + [] { } \ | ; : ' " , . < > / ? space).
- IPMI and iDRAC Users** - Service login passwords must be between 8-20 characters, and must include at least one upper case (A-Z), one lowercase (a-z), one number (0-9), and one special character (` ~ ! @ # \$ % ^ & * () - _ = + [] { } \ | ; : ' " , . < > / ? space).

Product Compatibility List

The following table provides information about DXi hardware compatibility with DXi 4.9 Software.

Component	Description
DXi4800	<ul style="list-style-type: none"> • 1 Node • 1 to 2 RAID controller cards. • 0 to 4 Expansion modules (JBODs) • 1 x 1 GbE Ethernet ports • (Optional) 2 x 10 GbE Ethernet ports • (Optional) Up to 8 x 25 GbE Ethernet ports (SFP28 optical or DAC Copper) • (Optional) Up to 16 x 10 GbE SFP Ethernet ports or 16 x 10GbE Base-T Ethernet ports. • (Optional) Up to 16 x 16 Gb Fibre Channel ports (for VTL or PTT) • (Optional) Up to 8 x 100 GbE Ethernet ports (Optical or DAC Copper) • 8 TB - 315 TB usable capacity
DXi9000 SD	<ul style="list-style-type: none"> • 1 Node • 1 Array module (RBOD) • 0 to 9 Expansion modules (EBODs) • 1 x 1 GbE Ethernet ports • (Optional) 2 x 10 GbE Ethernet ports • (Optional) Up to 8 x 25 GbE Ethernet ports (SFP28 optical or DAC Copper) • (Optional) Up to 16 x 10 GbE SFP Ethernet ports or 16 x 10GbE Base-T Ethernet ports. • (Optional) Up to 16 x 16 Gb Fibre Channel ports (for VTL or PTT) • (Optional) Up to 8 x 100 GbE Ethernet ports (Optical or DAC Copper) • 51 TB - 1020 TB usable capacity

Component	Description
DXI9000 HD	<ul style="list-style-type: none"> • 1 Node • 1 Array module (RBOD) • 1 Expansion module (EBOD) • 1 x 1 GbE Ethernet ports • (Optional) 2 x 10 GbE Ethernet ports • (Optional) Up to 8 x 25 GbE Ethernet ports (SFP28 optical or DAC Copper) • (Optional) Up to 16 x 10 GbE SFP Ethernet ports or 16 x 10GbE Base-T Ethernet ports. • (Optional) Up to 16 x 16 Gb Fibre Channel ports (for VTL or PTT) • (Optional) Up to 8 x 100 GbE Ethernet ports (Optical or DAC Copper) • 204 TB - 1020 TB usable capacity
DXI9100	<ul style="list-style-type: none"> • 1 Node • 1-2 Array modules (RBODs) • 0-2 Expansion modules (EBODs) • 1 x 1 GbE Ethernet ports • 2 x 10 GbE Ethernet ports • (Optional) 2 x 10 GbE Ethernet ports • (Optional) Up to 8 x 25 GbE Ethernet ports (SFP28 optical or DAC Copper) • (Optional) Up to 16 x 10 GbE SFP Ethernet ports or 16 x 10GbE Base-T Ethernet ports. • (Optional) Up to 16 x 16 Gb Fibre Channel ports (for VTL or PTT) • (Optional) Up to 8 x 100 GbE Ethernet ports (Optical or DAC Copper) • 204 TB - 2 PB usable capacity

Resolved Issues

The following issues were resolved in DXi 4.9 Software.

Issue Number	Description	Customer Number
DXE-16694	Replication unresponsive during I/O operations.	570741
		612643
		634081
		637097
		637216
		637933
		637931
		647588
		650204
		653149
		653865
		6753365
		684820
		683432
		721092
		722362
DXE-17958	Syscli over SSH credential token invalid issue.	734953
		742431
		745487
		562191
DXE-18815	DART memory issue.	715551
		682143
		714288
		726043
DXE-18815	DART memory issue.	604598
		680651

Issue Number	Description	Customer Number
DXE-26776	Timeout expanded for <i>Send Job Status</i> and <i>Target DXi</i> on the <i>Replication</i> page.	717570
DXE-26921	Secure snapshot timeout issues.	735025

Known Issues

DXi 4.9 Software has the following known issues:

Issue Number	Description
DXE-25942	DART GUI banner does not display full firmware version. DART (DXi Advanced Reporting) GUI does not contain enough space to display the new full firmware version. The firmware version has changed due to use of Git code build methods. The DXi code version can still be obtained from the DART GUI.
DXE-20388	Large DXi with extremely busy non-dedup Shares can cause Health Check and Garbage Collection to slow and use excess memory. Workaround: use dedup enabled shares. (DXi is not meant to be a primary storage device.)
DXE-26006	GUI: Can not return to home page from Disk Usage page. Customers using DXi4800 and ingesting data may be unable to navigate from the <i>GUI Status > Disk Usage</i> page to the GUI Home page. Workaround: Navigate to another GUI page and then navigate to the Home page.
DXE-26043	Netserver is not working properly. Usually this function is used in conjunction with Service to test the network connection from one DXi to another. Netserver is not used for any data storage functionality.
DXE-26082	Status page showed network ports p5p3 and p5p4 down with attention mode after successfully upgrading from 4.6.0-build1 to 4.8.0-build8. There is no functional impact to the DXi. Quantum Service can remove the attention after upgrade.
DXE-26091	CLI: Secure Email: CLI (Command Line Interface) command needs improvement. Parameters and values names are not consistent. No functionality impact. Some inconsistencies and improvements that could be made in a future release.
DXE-27624	Upon upgrade to 4.9.0, a V5000 maybe appear to hang and never reach the "Normal" state. In this case, the user needs to log in to the V5000 desktop and respond to the <i>Select Hardware Profile</i> dialog. It is recommended to select the "Small" profile as it best matches V5000s created before 4.9.0.

Documentation

For the latest DXi V5000, DXi4800, and DXi9000 Series documentation using DXi 4.9 software, see the following DXi Documentation Centers:

- **DXi V5000 Documentation Center:** www.quantum.com/dxiv5000docs
- **DXi4800 Documentation Center:** www.quantum.com/DXi4800Docs
- **DXi9000 Series Documentation Center:** www.quantum.com/DXi9000Docs

Supported Backup Applications

For the current list of backup applications supported for use with DXi 4.9 Software:

1. Click on <https://www.quantum.com/swcompguide.aspx>

The **Support > Software Compatibility With Tape Libraries** page appears.

2. In the **Compatibility Guide** list, select **Software / Disk-Based Backup Systems**.
3. (Optional) Select your system and software from the **Storage Device** and **Application Software** lists.

i Note: If the storage device and application software are not selected, a full list of all available devices and software will appear and requires a minute or two to populate. Select your system and software for a faster-appearing, shorter list.

4. Click **Submit**.

i Note: Contact the backup application vendor for the latest software revision information.

DXi Additional Notes

Email Reports

Quantum recommends enabling **Email Reports** after upgrading to DXi 4.9 Software (if not already enabled). When enabled, **Email Reports** periodically sends system configuration and status information to Quantum, including any software upgrades you have installed using the **Software Upgrade Utility**. Quantum Support can use this information to provide a better support experience in the future.

To configure Email Reports:

1. Make sure a valid outgoing e-mail server is specified on the **Configuration > Notifications > Email > Server** page.
2. (Optional) Specify any additional recipients to receive the reports on the **Configuration > Notifications > Email > Email Reports > Recipients** page.
3. Make sure a weekly **Email Reports** schedule is configured on the **Configuration > Scheduler** page. Configure two weekly recurring events: one for **Status** reports and one for **Configuration** reports.

Contacting Quantum

More information about this product is available on the Service and Support website at <https://www.quantum.com/en/service-support/>. The Service and Support website contains a collection of information, including answers to frequently asked questions (FAQs). You can also access software, firmware, and drivers through this site.

For further assistance, or if training is desired, contact the Quantum Customer Support Center:

Region	Support Contact
North America	1-800-284-5101 (toll free) +1-720-249-5700
EMEA	+800-7826-8888 (toll free) +49 6131 324 185
Asia Pacific	+800-7826-8887 (toll free) +603-7953-3010

For worldwide support:

<https://www.quantum.com/en/company/contact-us/>
